

**230V AC Base for Sounder Roshni-LP and Beacon Solex 3/10**

**Description:**

The base with integrated power supply unit makes it possible to connect sounder and beacon to mains supply. The base is designed for external use.

**Technical Data:**

|                              |                          |
|------------------------------|--------------------------|
| Input Voltage:               | 86 - 264V AC @ 50-60Hz   |
| Output Voltage:              | 24V DC                   |
| Output Current:              | 100mA max.               |
| Cable Size:                  | max. 2,5 mm <sup>2</sup> |
| Operating Temperature Range: | -25°C ... +55°C          |
| Type of Protection:          | IP 65                    |
| Material:                    | ABS FR, red RAL 3001     |
| Weight:                      | 0,1 kg                   |



**Compatible with:**

Roshni LP, Roshni LP Maxi, Flashni, Solex, Solista, Clarifire

**Order details**

| Description       | Part-No      | Remarks          |
|-------------------|--------------|------------------|
| Powered Deep Base | K0 245 540 8 |                  |
| Sounder Roshni-LP | K0 245 540 7 | c/w shallow base |
| Beacon Solex 10   | K0 245 544 8 | c/w shallow base |

